

7-1 CK2085VR5X/BWT (CK2173VR5X AND CK2085VR5X Dissimilar Parts)

7-2 CK2185VR5S/AWT (CK2173VR5X AND CK2185VR5S Dissimilar Parts)

Samsung Electronics

7-4 CK20E3VR5X/NWT (CK2173VR5X AND CK20E3VR5X Dissimilar Parts)

7-2

7-5 CK2073XR5X/VWT (CK2173VR5X AND CK2073XR5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT) BUYER : SESPO				RT13	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				RW701	2011-001133	R-NETWORK;33K/24K/75x3,5%,1/8W,X,SIP,6P,	
				RW901	2011-000531	R-NETWORK;4.7KOHM,5%,1/8W,A,SIP,8PBK	
				△ TU01	AA40-10006Q	TUNER-V/S;TELE4-125A,PAL-B/G,TR,181CH	
				X901	2801-001476	CRYSTAL-UNIT;12.0MHz,50ppm,28-ABQ,S,30ohm,T	
* AA94-00667A ASSY-PCB,MAIN(OPT);CK2073XR5X/VWT,S15A,LITHUANIA,				ASSY-CRT			
C227	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5		△	AA03-10030T	CRT-COLOR;- ,A48ECR41X02,+380mG,20,90deg	
C253	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,		REMOCON			
C254	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,					
C255	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,					
C409	2306-000253	C-FILM,MPPF;7.2nF,5%,1.6KV,TP,28.5x18.5x12					
C410	2201-000984	C-CERAMIC,DISC;680pF,10%,2KV,Y5P,TP,11x6,7.5mm					
C908	2201-000980	C-CERAMIC,DISC;30pF,5%,50V,CH,TP,5.0x3.0,5mm					
C909	2201-000980	C-CERAMIC,DISC;30pF,5%,50V,CH,TP,5.0x3.0,5mm					
C916	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm					
C928	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm					
CN802	AA27-20003Y	COIL-DEGAUSSING;- ,20',200HM,35T,L2170,E					
CT01	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.					
CT02	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.					
CT03	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5					
CT04	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.					
CT05	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP,3.5x19,-					
CT06	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.					
CT07	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5					
D903	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP					
D905	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
D910	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP					
D911	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP					
DT01	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
DT02	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
DT03	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
DZ806	0403-000355	DIODE-ZENER;UZ5.1BSB,5.1V,4.97-5.18V,500mW					
DZ902	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,					
△ IC802	1203-000644	IC-POS.FIXED REG.;7630,SIP,10P,-,PLASTIC,5.1/8V,					
△ IC901	AA13-30019HIC-MCU;- ,SPM-175ER(097),8BIT,SDIP,CK5385T,52P,600MIL						
J149	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm					
J175	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM					
J176	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM					
J178	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM					
LT01	2901-000297	FILTER-EMI ON BOARD;- ,3A,-,-,3.5x5,TP,-					
LT02	2901-000297	FILTER-EMI ON BOARD;- ,3A,-,-,3.5x5,TP,-					
LT03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm					
Q251	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100					
Q902	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100					
QT02	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100					
QT03	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,TP					
R205	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R220	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R250	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R301	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.4					
R305	2001-001048	R-CARBON(S);1.2OHM,5%,1/2W,AA,TP,2.4X6.4MM					
R820	2008-001062	R-FUSIBLE;39ohm,5%,2W,AF,TP,3.9x10mm					
R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R907	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R908	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R909	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R921	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4MM					
R932	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R933	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R935	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R939	2001-000006	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R944	2001-000006	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R958	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R959	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT01	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT03	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT04	2008-001062	R-FUSIBLE;39ohm,5%,2W,AF,TP,3.9x10mm					
RT05	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT06	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT07	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT08	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT09	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM					

7-6 CK2173VR5X Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT) BUYER : SRSC				C604	2401-001323	C-AL;470nF,20%,50V,BP,TP,5x11,5mm	
* AA94-00765A ASSY-PCB,MAIN(OPT);CK2173VR5X/BWT,S15A,RUSSIA				C610	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
C101	2401-000030	C-AL;22uF,20%,25V,GP,TP,5x11,5		C613	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C102	2401-001082	C-AL;330nF,20%,50V,GP,TP,5x11,5		C614	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP,1.9x3.5,7	
C103	2401-001363	C-AL;470uF,20%,16V,GP,TP,10x12.5,5		C702	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP,3.5x19,-	
C201	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,		C705	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C202	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C203	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5		C800	2306-000321	C-FILM,MPPF;470nF,5%,275V,TP,-,22.5	
C204	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		C801	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
C205	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5mm,		C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
C206	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5mm,		C803	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C207	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm		C804	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5.5	
C208	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C805	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.5	
C209	2202-000849	C-CERAMIC,MLC-AXIAL;18pF,5%,50V,CH,TP,3.5x1.9,-		C806	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,18x8,10m	
C210	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C807	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,TP,13x7,7.5	
C211	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm,		C808	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
C212	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-		C809	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
C213	2201-000273	C-CERAMIC,DISC;18pF,5%,50V,CH,TP,5x3mm,5		C810	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,TP,13x7,7.5	
C214	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5mm		C811	2401-003141	C-AL;2200uF,20%,25V,WT,TP,13x25,5mm	
C215	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm		C814	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C815	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
C217	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		C816	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		C818	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C221	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP,1.9x3.5,-		C819	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C222	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		C901	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C224	2202-000295	C-CERAMIC,MLC-AXIAL;68pF,5%,50V,SL,TP,3.5x19,-		C902	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C226	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5m		C904	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C228	2201-000247	C-CERAMIC,DISC;15pF,5%,50V,CH,TP,5x3,5		C905	2401-001333	C-AL;470nF,20%,50V,GP,TP,5x11,5	
C230	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5		C907	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,8x3.5	
C231	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		C908	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,5	
C232	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C909	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,5	
C238	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5		C910	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C239	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C911	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm,		C912	2201-000234	C-CERAMIC,DISC;150pF,5%,50V,CH,TP,9.5x3,5	
C247	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		C913	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm,	
C248	2309-000138	C-FILM,PEF;100nF,5%,50V,TP,20x16x8.5,7.5m		C914	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C249	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		C915	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C250	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5m		C916	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5m	
C251	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,5		C917	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	
C252	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		C919	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C301	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		C920	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
C302	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		C922	2201-000573	C-CERAMIC,DISC;47pF,5%,50V,CH,TP,6.5x3.0,5	
C303	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5		C923	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	
C304	2401-000903	C-AL;22uF,20%,160V,WT,TP,10x20mm,5m		C924	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	
C305	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm		C926	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C306	2305-000285	C-FILM,MPEF;220nF,5%,100V,TP,10.5X5.5X15MM		C927	2201-000573	C-CERAMIC,DISC;47pF,5%,50V,CH,TP,6.5x3.0,5	
C307	2305-000708	C-FILM,MPEF;150nF,5%,100V,TP,16.5x10.3x5.7		CA01	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C308	2305-000450	C-FILM,MPEF;56nF,5%,100V,TP,-,5mm		CN501	AA39-20109B	LEAD-CONNECTOR,ASSY,-,YBNH025-08,S,8P,500,1007#26	
C401	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm		CN601	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGHT,SN	
C402	2201-000599	C-CERAMIC,DISC;560pF,10%,500V,Y5P,TP,7x4,5		CN703	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGHT,SN	
C403	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4,5		CN802	AA27-20003Z	COIL-DEGAUSSING,-,21',20.5OHM,35T,L2380,E	
C404	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm		CW901	2503-000156	C-NETWORK;100pF,4,20%,50V	
C408	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5		D201	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C409	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2		D202	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C410	2201-000983	C-CERAMIC,DISC;1nF,10%,2KV,Y5P,TP,13x6,7.5mm		D205	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C411	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5		D208	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C413	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm		D209	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C414	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.5		D210	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C415	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5		D211	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C416	2306-000204	C-FILM,MPPF;430nF,5%,400V,TP,26x20.5x12.5,		D213	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP	
C417	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4,5		D401	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C418	2401-000384	C-AL;10uF,20%,100V,GP,TP,6.3x11,5mm		D402	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C419	2201-000984	C-CERAMIC,DISC;680pF,10%,2KV,Y5P,TP,11x6,7.5m		D403	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5		D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,TP	
C503	2201-002063	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,16x5,7		D405	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5		D406	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m		D501	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204	
C601	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP,1.9x3.5,7		D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C602	2401-000030	C-AL;22uF,20%,25V,GP,TP,5x11,5		D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C603	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm		D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
				D800	1405-000187	VARIATOR;750V,1250A,12.5x7mm,TP	
				D801	0402-000102	DIODE-BRIDGE;D2SB60,600V,1.5A,-	
				D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
				D804	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41,TP	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
D805	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,TP		PC801	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
D809	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q201	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D810	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204		Q202	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D901	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q204	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D903	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q401	0502-001115	TR-POWER;KSC5386,NPN,50W,TO-3PF,ST,8-	
D905	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
D906	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q701	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D907	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q901	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D908	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q903	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
D910	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		Q904	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,TP	
D912	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q905	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,TP	
DA01	0401-000005	DIODE-SWITCHING;1N4148,75V,200MA,DO-35,TP		Q906	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,TP	
DZ201	0403-000355	DIODE-ZENER;UZ5.1BSB,5.1V,4.97-5.18V,500mW		Q907	0504-000125	TR-DIGITAL;KSR1012,NPN,300mW,47K,TO-92,TP	
DZ202	0403-000551	DIODE-ZENER;MTZ3.9B,3.9V,3.89-4.16V,500mW,		Q908	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,TP	
DZ203	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		QA01	0501-002183	TR-SMALL SIGNAL;KTC9014,NPN,625mW,TO-92,TP,100	
DZ204	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		R200	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ205	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R201	2001-000005	R-CARBON;390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ208	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R202	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ301	0403-000660	DIODE-ZENER;MTZ22A,22V,20.15-21.2V,500mW,D		R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ302	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,TP		R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ401	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		R207	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ501	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R208	2001-000005	R-CARBON;390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ502	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R209	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
DZ503	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R210	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ504	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R211	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ704	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R212	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ802	0403-000297	DIODE-ZENER;MTZ6.2B,6.2V,5.96-6.27V,500mW,		R213	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ803	1203-001217	IC-POS.I.ADJUST REG.;431,TO-92,3P,4.58MIL,PLASTIC,2		R214	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ804	2001-001170	R-CARBON(S);6.8KOHM,5%,1/2W,AA,TP,2.4X6.4MM		R215	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
DZ808	0403-000300	DIODE-ZENER;MTZ8.2B,8.2V,7.78-8.19V,500mW,		R216	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ809	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		R217	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
DZ901	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW,		R218	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
DZ902	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V,TP,-,7.5		R219	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ903	1203-000451	IC-VOLTAGE REGULATOR;33,TO-92,3P,-,PLASTIC,31/35V,		R221	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ905	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		R223	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ907	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		R224	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ909	0403-000551	DIODE-ZENER;MTZ3.9B,3.9V,3.89-4.16V,500mW,		R225	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
F801	3601-000261	FUSE-FERRULE;250V,3.15A,TL,GLASS,5.2x20mm		R226	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
F801A	3602-000114	FUSE-HOLDER,-,30mohm		R227	2004-001234	R-METAL;75Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
F801B	3602-000114	FUSE-HOLDER,-,30mohm		R229	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
F802	3601-001086	FUSE-FERRULE;125V,5A,FA,GLASS,2.4x7.5mm		R230	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC201	1204-001440	IC-VIDEO SYSTEM;TDA8842,DIP,56P,300MIL,PLASTIC		R231	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC301	1204-000441	IC-IF CIRCUIT;TDA8356,SIP,9P,-,PLASTIC,40V,-		R232	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2M	
IC501	1201-001159	IC-VIDEO AMP;6107,ZIP,9P,300MIL,SINGLE,-,PL		R234	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC601	1201-001147	IC-AUDIO AMP;7056B,SIP,9P,-,SINGLE,41.5dB,P		R236	2003-000634	R-METAL OXIDE(S);3.9Kohm,5%,1W,AA,TP,3.9x9mm	
IC801	1203-001494	IC-PWM CONTROLLER;3S0680RF,TO3PF-5L,5,210,PLASTI		R237	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC802	1203-001531	IC-POS.FIXED REG.;7630,SIP,10P,-,PLASTIC,5.1/8V,		R240	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC901	AA13-30021J	IC-MCU;-S2M-173ER3(R3943),8BIT,ST,SD		R241	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
IC902	1103-001105	IC-EEPROM;24C040,4Kx1BIT,DIP,8P,300MIL,1		R242	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
J181	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R251	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
J185	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		R252	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
JS701	3722-000497	JACK-PIN;4P,3.4mm,SN,BLK,-		R262	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L102	2701-000212	INDUCTOR-AXIAL;68uH,10%,2.8x7mm		R301	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		R302	2008-001033	R-FUSIBLE(S);10ohm,5%,2W,AF,TP,3.9x10mm	
L202	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm		R303	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L206	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		R305	2004-001370	R-METAL(S);1.3ohm,1%,1/2W,AA,TP,2.4x6.4mm	
L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		R306	2008-000254	R-FUSIBLE(S);0.68ohm,5%,2W,AF,TP,3.9x10mm	
L302	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		R307	2003-001026	R-METAL OXIDE(S);180ohm,5%,2W,AF,TP,3.9x10mm	
L304	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm		R402	2003-000664	R-METAL OXIDE(S);33ohm,5%,2W,AF,TP,4x12mm	
L305	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm		R403	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L306	2701-000115	INDUCTOR-AXIAL;10uH,10%,2.8x7mm		R404	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
L401	AA27-30001B	COIL-LINEARITY;-195uH,QIC1010,PI0,4,4.5x21.5		R405	2001-001410	R-CARBON(S);43OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L402	2901-000297	FILTER-EMI ON BOARD;-3A,-,3.5x5,TP-		R406	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L601	2701-000146	INDUCTOR-AXIAL;2.2uH,10%,2.5x3.4mm		R407	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.4M	
L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm		R408	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm		R409	2008-000204	R-FUSIBLE(S);0.22ohm,10%,1/2W,AF,TP,2.5x6.5	
L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm		R412	2003-000664	R-METAL OXIDE(S);33ohm,5%,2W,AF,TP,4x12mm	
L801	AA29-30001B	FILTER-LINE;-27mH,-,--		R413	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x12mm	
L804	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,2400G		R414	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12mm	
L805	2901-000297	FILTER-EMI ON BOARD;-3A,-,3.5x5,TP-		R415	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5mm	
L807	2901-000297	FILTER-EMI ON BOARD;-3A,-,3.5x5,TP-		R416	2008-000277	R-FUSIBLE;68ohm,5%,1/2W,AA,TP,4.7x11mm	
L809	2701-001032	INDUCTOR-AXIAL;100uH,10%,5x14mm		R417	2008-000265	R-FUSIBLE(S);1ohm,5%,2W,AA,TP,3.9x10mm	
L810	2701-001032	INDUCTOR-AXIAL;100uH,10%,5x14mm		R420	2004-001377	R-METAL(S);120Kohm,1%,1/2W,AA,TP,2.4x6.4m	
L902	2701-000189	INDUCTOR-AXIAL;470nH,10%,2.5x3.4mm		R501H	2002-001008	R-COMPOSITION;1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
L904	2701-000299	INDUCTOR-AXIAL;13uH,10%,2.5x3.4mm		R502H	2002-001008	R-COMPOSITION;1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
LD901	AA96-30007A	ASSY-LED,GUIDE;-AA61-50055A,DL-G7GA,GREEN		R503	2002-001008	R-COMPOSITION;1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
NT801	1404-001075	THERMISTOR-NTC;5ohm,15%,-,17mW/C,TP		R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4MM	
P801	1404-001048	THERMISTOR-PTC;7ohm,30%,200/220V,270V,19A,-,B		R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10mm	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RA03	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RA04	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RL901	AA59-60001U	MODULE-REMOCON;- ,ORC-50VF/SR-12V,38KHz,940nm,	
R603	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		RW702	2011-001098	R-NETWORK;75/75/1K/75OHM,5%,1/8W,- ,SIP5	
R604	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		RX801	2002-001011	R-COMPOSITION;3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R610	2001-000347	R-CARBON;13KOHM,5%,1/8W,AA,TP,1.8X3.2MM		SFN02	2904-001063	FILTER-SAW AV:38.9MHz,SIP5K,TP,17dB,PAL-B/G,	
R611	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		SW801	3403-000179	SWITCH-PUSH;250V,5A,DPST,- ,JPW-2104B	
R701	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SPST	
R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SPST	
R706	2001-000812	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SPST	
R714	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SPST	
R715	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SPST	
R717	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		△ T401	AA26-50001B	HORIZ.DRIVE;- ,7.1mH,102uH,10-20uH,YL081,ST	
R801	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x10mm		△ T444	AA26-30001Y	TRANS-FLYBACK;- ,FSV-20A001,20,125V	
R802	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x10mm		△ T801	AA26-20007Q	TRANS-SWITCHING;- ,180-260V,125V/12.5V,EN,EER28	
R803	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4x6.4MM		△ TU01	AA40-10006P	TUNER-V/S;TECC0949VG28B(S),PAL-B/G,TR,18	
R805	2001-001134	R-CARBON(S);360ohm,5%,1/2W,AA,BK,2.4x6.4mm		△ V999	3704-001090	SOCKET-CRT;9P,15.24PI,26.5PI,SN,-	
R806	2002-001011	R-COMPOSITION;3.3Mohm,10%,1/2W,AA,TP,3.7x9mm		X202	2801-000226	CRYSTAL-UNIT;3.579545MHz,20ppm,28-AAM,15pF	
R807	2002-001011	R-COMPOSITION;3.3Mohm,10%,1/2W,AA,TP,3.7x9mm		X203	2801-000274	CRYSTAL-UNIT;4.433619MHz,30ppm,28-AAM,20pF	
R808	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4x6.4MM		X901	2801-000724	CRYSTAL-UNIT;6MHz,50ppm,28-AAM,20pF,40ohm,T	
R809	2001-000622	R-CARBON;300KOHM,5%,1/8W,AA,TP,1.8X3.2M		Z201	2903-000199	FILTER-CERAMIC;TR,6.5MHz,70KHz,- ,TP-	
R810	2003-000527	R-METAL OXIDE(S);18Kohm,5%,2W,AA,TP,4x12mm		Z202	2903-000181	FILTER-CERAMIC;TR,5.5MHz,- ,TP,TPS5.5MB-TF	
R811	2001-001134	R-CARBON(S);360ohm,5%,1/2W,AA,BK,2.4x6.4mm		Z204	2903-000184	FILTER-CERAMIC;BP,5.5MHz,+60KHz,6dB,- ,TP-	
R812	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12mm		Z205	2903-000202	FILTER-CERAMIC;BP,6.5MHz,+80KHz,6dB,- ,TP-	
R814	2008-000267	R-FUSIBLE(S);2.4ohm,5%,2W,AA,TP,3.9x10mm		Z206	2903-000184	FILTER-CERAMIC;BP,5.5MHz,+60KHz,6dB,- ,TP-	
R815	2008-000267	R-FUSIBLE(S);2.4ohm,5%,2W,AA,TP,3.9x10mm		Z210	2903-000200	FILTER-CERAMIC;BP,6.5MHz,+70KHz,6dB,- ,TP-	
R816	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5m			AA39-20010D	LEAD-CONNECTOR,ASSY;- ,YFH800-01,S,1P,400,1617#22	
R817	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.4					
R818	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4m		*	AA95-90027D	ASSY-PCB,A/V FRONT;- ,CK5073,SCT13B,CE,9P,-	
R819	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		CE01	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
R820	2008-000299	R-FUSIBLE(S);47ohm,5%,2W,AF,TP,3.9x10mm		CE03	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
R821	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm		CE06	2202-000862	C-CERAMIC,MLC-AXIAL;390pF,10%,50V,Y5P,TP,3.5x1.9,-	
R822	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4x6.4M		CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP,- ,7.5	
R823	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4x6.4M		CN702	AA39-20112E	LEAD-CONNECTOR,ASSY;- ,YBNH025-09,67096-009,9P,300,	
R824	2001-001134	R-CARBON(S);360ohm,5%,1/2W,AA,BK,2.4x6.4mm		JA702	3722-000506	JACK-RCA;2P,3.6mm,- ,AG	
R825	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x10mm		JE601	3722-000143	JACK-PHONE;1P(VER),3.4mm,AG,BLK,NO	
R901	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM		LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
R902	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		QE01	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,TP,120-	
R903	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4x6.4MM	
R904	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE02	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4x6.4MM	
R905	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		RE03	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R906	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		RE04	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R908	2001-000232	R-CARBON;1.3KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R909	2001-000605	R-CARBON;3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R912	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R918	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R920	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R922	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R923	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R924	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R925	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R926	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R927	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R928	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4x6.4MM					
R929	2004-000253	R-METAL;11Kohm,1%,1/8W,AA,TP,1.8x3.2mm					
R930	2004-000218	R-METAL;10Kohm,1%,1/8W,AA,TP,1.8x3.2mm					
R931	2004-000218	R-METAL;10Kohm,1%,1/8W,AA,TP,1.8x3.2mm					
R934	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R936	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R937	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R938	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R940	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R946	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R947	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R948	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R951	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R952	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R954	2001-000006	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R956	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R960	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R962	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RA01	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RA02	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M					

ASSY-PCB,A/V FRONT

AA95-90027D ASSY-PCB,A/V FRONT;- ,CK5073,SCT13B,CE,9P,-

2401-001840 C-AL;100uF,20%,16V,GP,TP,6.3x11,5
 2401-001989 C-AL;4.7uF,20%,50V,BP,TP,5x11,5
 2202-000862 C-CERAMIC,MLC-AXIAL;390pF,10%,50V,Y5P,TP,3.5x1.9,-
 2202-000222 C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP,- ,7.5
 AA39-20112E LEAD-CONNECTOR,ASSY;- ,YBNH025-09,67096-009,9P,300,
 3722-000506 JACK-RCA;2P,3.6mm,- ,AG
 3722-000143 JACK-PHONE;1P(VER),3.4mm,AG,BLK,NO
 2701-000158 INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm
 0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,TP,120-
 2001-001153 R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4x6.4MM
 2001-001153 R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4x6.4MM
 2001-000010 R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM
 2001-000429 R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
 2001-000009 R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM

ASSY-POWER,CORD

AA39-10001G POWER-CORD;- ,KKP-419C,KLCE-2F,2.286m,HOUS
 AA61-20070A HOLDER-CORD;- ,PP,V0,BLK,KE-0002

REMOCON

AA59-10107N REMOCON;- ,TM59,SS,SZM173EA,24,- ,L/GR

ASSY-SPEAKER

3001-000003 SPEAKER;3W,16ohm,88+2dB,180+36Hz
 AA39-20501C LEAD CONNECTOR-ASSY;- ,67096-003,REC,3(2)P,700mm,10

ASSY-CRT

AA03-10024T CRT-COLOR;- ,A51KQJ63X(H),+380mG,21,90de
 AA27-00002A MAGNET-CONVERGENCE;- ,JH291-SC-OB,29,1MM
 AA27-50004K DEFLECTION-YOKE;- ,DST-2192ML(H1),21,S/T,2.28m
 AA63-60028A SPACER-DY;NEOPRENE,- ,BLK,V0 W12,-

ASSY-ACCESSORY

AA26-90001C TRANS-MATCHING;- ,300ohm/75ohm,PAL,40-890MHz
 AA42-10001V ANT-ROD;- ,3S,620mm,BRN,UL/CSA
 AA68-11259C MANUAL-USERS;S15A,RUSSIAN,1 COLOR,B5,W/P 10