

7. Electric Parts List

7-1 CK501FVR5S/NWT (CK331FVR5X AND CK501FVR5S Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
		ASSY-PCB,MAIN(OPT)				ASSY-ACCESSORY	
		BUYER : SRSC				AA68-11289A MANUAL-USERS;S15A,N-RUSSIA,W/O TTX,B5,W/P 1	
		AA94-00408A ASSY-PCB,MAIN(OPT);CK501FVR5S/NWT,S15A,N-RUSSIA,-				ASSY-CABINET;501F,CK501FVR5S/NWT	
		* AA94-00408A ASSY-PCB,MAIN(OPT);CK501FVR5S/NWT,S15A,N-RUSSIA,-				AA91-10389C ASSY-CABINET,FRONT:DP,CK501FVR,BK708P MLN TVI (SPK)	
C307	2305-000708	C-FILM,MPEF:150nF,5%,100V,TP,16.5x10.3x5.7				AA64-31093M CABINET-FRONT:-,CK501FVR,BK708P BWT TVI,HIPS	
C409	2306-000253	C-FILM,MPPF:7.2nF,5%,1.6KV,TP,28.5x18.5x12				AA64-31218B CABINET-BACK:DP,501F,AA64-31094B,-,V2,-,-,-	
C410	2201-000406	C-CERAMIC,DISC:270pF,10%,2KV,Y5P,TP,8x6,7.5				AA64-10759A KNOB-CONTROL:DP,501F,AA64-10705A,-,-,-	
C416	2306-000195	C-FILM,MPPF:360nF,5%,400V,TP,26x19x11.5,20				AA60-10050Q SCREW-ASSY:WC,HH,+,M5,L26.5,SWRCH18A,ZPC(
C916	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm				AA65-30107A CLAMP-D,COIL:NYLON 66,V2,NTR,-,20-22 INCH,-	
CN501	AA39-20109B	LEAD-CONNECTOR,ASSY:-,YBNH025-08,S,8P,500,1007#26				AA61-40053A STOPPER-PCB:ALL MODEL,HIPS HB,WHT,HB,-,-	
CN802	AA27-20003Y	COIL-DEGAUSSING:-,20,15.2ohm,28T,L2170,E				AA64-70015A BADGE-BRAND:AL,SS R2000 22,SILVER,L45,-,-,-	
L401	AA27-30001B	COIL-LINEARITY:-,195uH,QIC1010,PIO,4,4.5x21.5				6002-000514 SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
R302	2008-001033	R-FUSIBLE(S):10ohm,5%,2W,AF,TP,3.9x10mm					
R305	2004-001370	R-METAL(S):1.3ohm,1%,1/2W,AA,TP,2.4x6.4mm					
R405	2001-001410	R-CARBON(S):430HM,5%,1/2W,AA,TP,-					
R417	2008-000265	R-FUSIBLE(S):1ohm,5%,2W,AA,TP,3.9x10mm					
R501H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm					
R502H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm					
R505	2008-001011	R-FUSIBLE(S):0.18ohm,10%,2W,AF,TP,3.9x10mm					
R611	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,-					
R814	2008-000267	R-FUSIBLE(S):2.4ohm,5%,2W,AA,TP,3.9x10mm					
R815	2008-000267	R-FUSIBLE(S):2.4ohm,5%,2W,AA,TP,3.9x10mm					
T444	AA26-30001Y	TRANS-FLYBACK:-,FSV-20A001,20,125V					
V999	3704-001090	SOCKET-CRT;9P;15.24PI,26.5PI,SN,-					
		ASSY-CRT					
		AA03-10029WCRT-COLOR:-,A48KRD82X(H),+380mG,20,90de					
		AA27-00002A MAGNET-CONVERGENCE:-,JH291-SC-OB,29.1MM					
		AA27-50004W DEFLECTION-YOKE:-,DSE-1992LL(1H),20'/A48KRD82X					
		ASSY-SPEAKER					
		3001-000003 SPEAKER:3W,16ohm,88+-2dB,180+-36Hz					
		AA39-20501C LEAD CONNECTOR-ASSY:-,67096-003,REC,3(2P),700mm,10					

7-2 CK331FVR5X/BWT P arts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT)				C503	2201-002063	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,16x5,7	
BUYER : SRSC				C504	2401-001232	C-AL:4.7uF,20%,250V,GP,TP,10x12,5,5	
				C506	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
*	AA94-10136E	ASSY-PCB,MAIN(OPT):CK331FVR5X/BWT,S15A,RUSSIA,-		C601	2202-000210	C-CERAMIC,MLC-AXIAL:270pF,10%,50V,Y5P,TP,1.9x3.5,7	
*	AA94-00404A	ASSY-PCB,MAIN(OPT):CK331FVR5S/NWT,S15A,N-RUSSIA,-		C602	2401-000030	C-AL:22uF,20%,25V,GP,TP,5x11,5	
*	AA94-00418A	ASSY-PCB,MAIN(OPT):CK331FVR5X/VWT,S15A,LITHUANIA		C603	2301-000445	C-FILM,MPPF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C101	2401-000030	C-AL:22uF,20%,25V,GP,TP,5x11,5		C604	2401-001323	C-AL:470nF,20%,50V,BP,TP,5x11,5mm	
C102	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5		C610	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10x20,5mm	
C103	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12,5,5		C613	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C201	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C614	2202-000210	C-CERAMIC,MLC-AXIAL:270pF,10%,50V,Y5P,TP,1.9x3.5,7	
C202	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C702	2202-000263	C-CERAMIC,MLC-AXIAL:470pF,10%,50V,Y5P,TP,3.5x1.9,-	
C203	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		C704	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP,1.9x3.5,-	
C204	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C705	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C205	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C706	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C206	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C800	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-22.5	
C207	2305-000196	C-FILM,MPEF:150nF,5%,63V,TP,-5mm		C801	2401-002213	C-AL:150uF,+30-10%,450V,GP,BK,25x35	
C208	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		C802	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11,5	
C209	2202-000849	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.5x1.9,-		C803	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C210	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C804	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5.5	
C211	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,		C805	2303-000163	C-FILM,PPF:2.2nF,5%,800V,TP,15x13x8.5,7.5	
C212	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-		C806	2201-000446	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,18x8,10m	
C213	2201-000273	C-CERAMIC,DISC:18pF,5%,50V,CH,TP,5x3mm,5		C807	2201-000991	C-CERAMIC,DISC:560pF,10%,2KV,Y5P,TP,13x7,7.5	
C214	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5mm		C808	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5	
C215	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		C809	2401-002290	C-AL:47uF,20%,160V,GP,TP,13x20,5	
C216	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		C810	2201-000991	C-CERAMIC,DISC:560pF,10%,2KV,Y5P,TP,13x7,7.5	
C217	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C811	2401-003141	C-AL:2200uF,20%,25V,WT,TP,13x25,5mm	
C219	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C814	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C221	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP,1.9x3.5,-		C815	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11,5,5	
C222	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C816	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C224	2202-000295	C-CERAMIC,MLC-AXIAL:68pF,5%,50V,SL,TP,3.5x1.9,-		C818	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C226	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		C819	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C228	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		C901	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C230	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		C902	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C231	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C904	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C232	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C905	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5	
C238	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		C907	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,8x3.5	
C239	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		C908	2201-000193	C-CERAMIC,DISC:100pF,0.3pF,50V,CH,TP,5x3,5	
C240	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,		C909	2201-000193	C-CERAMIC,DISC:100pF,0.3pF,50V,CH,TP,5x3,5	
C247	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C910	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C248	2309-000138	C-FILM,PE-PPF:100nF,5%,50V,TP,20x16x8.5,7.5mm		C911	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
C249	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C912	2201-000234	C-CERAMIC,DISC:150pF,5%,50V,CH,TP,9.5x3,5	
C250	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		C913	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm,	
C251	2301-000204	C-FILM,PEF:2.7nF,5%,50V,TP,7.4x3.9x13mm,5		C914	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C252	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C915	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C253	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C916	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C254	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C917	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C255	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C919	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C301	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		C920	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C302	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		C922	2401-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0,5	
C303	2401-003028	C-AL:100uF,20%,25V,WT,TP,6.3x11,5		C923	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C304	2401-000903	C-AL:22uF,20%,160V,WT,TP,10x20mm,5m		C924	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C305	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-5mm		C926	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C306	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,10.5X5.5X15MM,5		C927	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0,5	
C307	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5,5		CA01	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C308	2305-000450	C-FILM,MPEF:56nF,5%,100V,TP,-5mm		CN501	AA39-20109A	LEAD-CONNECTOR,ASSY,-,YBNH025-08,S,8P,400,1007#26	
C401	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		CN601	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGHT,SN	
C402	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		CN802	AA27-20003U	COIL-DEGAUSSING:-,14,16.4ohm,75T,890mm,D	
C403	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		CW901	2503-000156	C-NETWORK:100pF,4,20%,50V	
C404	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10x20,5mm		D201	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C408	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		D202	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C409	2301-001219	C-FILM,MPE-PPF:3.9nF,5%,1.6KV,TP,29x8.5x15,20		D205	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C410	2201-000467	C-CERAMIC,DISC:330pF,10%,2KV,Y5P,TP,8x6,7.5		D208	2001-000633	R-CARBON:30KOHM,5%,1/8W,AA,TP-	
C411	2401-000927	C-AL:22uF,20%,250V,GP,TP,13x20,5		D209	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C413	2305-000382	C-FILM,MPEF:4.7nF,5%,400V,TP,-5mm		D210	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C414	2301-001065	C-FILM,MPPF:47nF,5%,630V,TP,19x15.5x7,7.5		D211	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C415	2401-000560	C-AL:1uF,20%,160V,GP,TP,6.3x11,5		D213	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C416	2306-001004	C-FILM,MPPF:300nF,5%,400V,TP,26x14x21mm,20		D401	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C417	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		D402	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C418	2401-000384	C-AL:10uF,20%,100V,GP,TP,6.3x11,5mm		D403	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C419	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7.5mm		D404	0402-000534	DIODE-RECTIFIER:RG10V,400V,1.2A,DO-201,TP	
C502	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11,7,5		D405	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
				D406	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
				D501	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
D502	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP		L801	AA29-30001B	FILTER-LINE-,-,27mH,-,-,-	
D503	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP		L804	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
D504	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP		L805	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
D701	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L807	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
D800	1405-000187	VARISTOR:750V,1250A,12.5x7mm,TP		L809	2701-001032	INDUCTOR-AXIAL:100uH,10%,5x14mm	
D801	0402-000102	DIODE-BRIDGE:D2SB60,600V,1.5A,-		L810	2701-001032	INDUCTOR-AXIAL:100uH,10%,5x14mm	
D802	0402-000540	DIODE-RECTIFIER:RU20A,600V,1.5A,-,TP		L902	2701-000189	INDUCTOR-AXIAL:470nH,10%,2.5x3.4mm	
D804	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41,TP		L904	2701-000299	INDUCTOR-AXIAL:13uH,10%,2.5x3.4mm	
D805	0402-000534	DIODE-RECTIFIER:RG10V,400V,1.2A,DO-201,TP		LD901	AA96-30007A	ASSY-LED,GUIDE:-,AA61-50055A,DL-G7GA,GREEN	
D809	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		NT801	1404-001075	THERMISTOR-NTC:5ohm,15%,-,17mW/C,TP	
D810	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204		P801	1404-001048	THERMISTOR-PTC:7ohm,30%,200/220V,270V,19A,-,B	
D901	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		PC801	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST	
D903	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		Q201	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
D905	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		Q202	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
D906	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		Q204	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
D907	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		△ Q401	0502-001115	TR-POWER:KSC5386,NPN,50W,TO-3PF,ST,8-	
D908	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		△ Q402	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,-,120-	
D910	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-		Q701	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
DA01	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		Q703	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-	
DZ201	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500mW		Q901	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
DZ202	0403-000551	DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500mW		Q902	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
DZ203	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		Q903	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
DZ204	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,-		Q904	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
DZ205	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		Q905	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
DZ208	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		Q906	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
DZ301	0403-000660	DIODE-ZENER:MTZ22A,22V,20.15-21.2V,500mW,D		Q907	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP	
DZ302	0403-001039	DIODE-ZENER:MA2560,56V,52-60V,1W,DO-41,TP		Q908	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
DZ401	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW		QA01	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100	
DZ501	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R200	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-	
DZ502	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R201	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,-	
DZ503	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R202	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ504	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R203	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ701	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R204	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ702	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R207	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,-	
DZ703	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R208	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,-	
DZ704	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R209	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ705	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R210	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
DZ802	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500mW		R211	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,-	
DZ803	1203-001217	IC-POSJ.ADJUST REG.:431,TO-92,3P,4.58MIL,PLASTIC,2		R212	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ804	2001-001170	R-CARBON(S):6.8KOHM,5%,1/2W,AA,TP,-		R213	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ808	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500mW		R214	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
DZ809	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW		R215	2001-001015	R-CARBON:9.1KOHM,5%,1/8W,AA,TP,-	
DZ901	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW		R216	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,-	
DZ903	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLASTIC,31/35V,2		R217	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
DZ905	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW		R218	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,-	
DZ907	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW		R219	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,-	
DZ909	0403-000551	DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500mW		R221	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
△ F801	3601-000261	FUSE-FERRULE:250V,3.15A,TL,GLASS,5.2x20mm		R223	2001-000938	R-CARBON:68OHM,5%,1/8W,AA,TP,-	
F801A	3602-000114	FUSE-HOLDER:-,-,30mohm		R224	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,-	
F801B	3602-000114	FUSE-HOLDER:-,-,30mohm		R225	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,-	
△ F802	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm		R226	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
△ IC201	1204-001440	IC-VIDEO SYSTEM:TDA8842,DIP,56P,300MIL,PLASTIC		R227	2004-001234	R-METAL:75Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
△ IC301	1204-000441	IC-IF CIRCUIT:TDA8356,SIP,9P,-,PLASTIC,40V,-		R229	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,-	
△ IC501	1201-001159	IC-VIDEO AMP:6107,ZIP,9P,300MIL,SINGLE,-,PL		R230	2001-000793	R-CARBON:47OHM,5%,1/8W,AA,TP,-	
△ IC601	1201-001147	IC-AUDIO AMP:7056B,SIP,9P,-,SINGLE,41.5dB,P		R231	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,-	
△ IC801	1203-001494	IC-PWM CONTROLLER:3S0680RF,TO3PF-5L,5,210,PLASTI		R232	2001-000356	R-CARBON:150KOHM,5%,1/8W,AA,TP,-	
△ IC802	1203-001531	IC-POSJ.FIXED REG.:7630,SIP,10P,-,PLASTIC,5.1/8V,		R234	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
△ IC901	AA13-30021J	IC-MCU:-,Z90233-R3943,8BIT,SDIP,CS-53		R236	2003-000634	R-METAL OXIDE(S):3.9Kohm,5%,1W,AA,TP,3.3x9mm	
△ IC902	1103-001105	IC-EEPROM:24C040,4Kx1BIT,DIP,8P,300MIL,1		R237	2001-000793	R-CARBON:47OHM,5%,1/8W,AA,TP,-	
J185	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R240	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,-	
JS701	3722-000183	JACK-SCART:21P,4mm,SN,BLK,NO		R241	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
L102	2701-000212	INDUCTOR-AXIAL:68uH,10%,2.8x7mm		R242	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
L103	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R251	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L202	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm		R252	2004-001914	R-METAL:39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
L206	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R262	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L301	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R301	2004-001983	R-METAL(S):2.49Kohm,1%,1/2W,AA,TP,2.4x6.4	
L302	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R302	2003-002010	R-METAL OXIDE(S):680ohm,5%,1W,AF,TP,3.9x10mm	
L304	2701-000159	INDUCTOR-AXIAL:22uH,10%,4.2x9.8mm		R303	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,-	
L305	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm		R305	2004-004087	R-METAL(S):1.5ohm,1%,1/2W,AA,TP,2.5x6.5mm	
L306	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R306	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm	
L401	AA27-30003R	COIL-LINERTY:-,220uH,YL10x10,0.35mm,23x13mm		R307	2003-000649	R-METAL OXIDE(S):330ohm,5%,1W,AF,TP,3.3x9mm	
L402	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R402	2003-000664	R-METAL OXIDE(S):33ohm,5%,2W,AF,TP,4x12mm	
L601	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm		R403	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,-	
L702	2701-000184	INDUCTOR-AXIAL:4.7uH,10%,2.5x3.4mm		R404	2008-000294	R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9x10mm	
L703	2701-000184	INDUCTOR-AXIAL:4.7uH,10%,2.5x3.4mm		R405	2001-000117	R-CARBON(S):68OHM,5%,1/2W,AA,TP,-	
L704	2701-000184	INDUCTOR-AXIAL:4.7uH,10%,2.5x3.4mm		R406	2001-000037	R-CARBON(S):330OHM,5%,1/2W,AA,TP,-	
L706	2701-000184	INDUCTOR-AXIAL:4.7uH,10%,2.5x3.4mm		R407	2001-001037	R-CARBON(S):0.390HM,5%,1/2W,AA,TP,-	

